AC Power for Business-Critical Continuity

Liebert GXT MT+ CX 1/2/3 kVA

Compact, Efficient and Reliable Back UP Power Solution









We are Fmerson

Emerson Network Power, a business of Emerson, a global company that leads by applying a unique combination of industry expertise, technology, and resources to make the future of our customers' enterprises and networks possible.

Emerson Network Power's broad technology base and global expertise support a full spectrum of enterprise wide solution for today's business needs. We have been providing tailored solutions for protecting the operation of critical electronic systems in virtually every business segment right from customer premise equipment to global network.

Emerson. Consider It Solved.

Customers call on Emerson when the stakes are the highest. Why?
Because they know that we bring them technology and engineering to create solutions for their success. Whatever their challenge, they know that with Emerson by their side, they can "Consider It Solved."



Supported by our right combination of knowledge, experience, product selection and service capability. We are the true solution provider of our customer's IT infrastructure, right from grid to chip level.

When the stakes are high, partner with Emerson Network Power to optimize your technology with "high-nines" reliability solutions specific to your infrastructure.

Liebert™ GXT-MT+ CX 1/2/3 kVA Compact, Efficient and Reliable Back UP Power Solution

Features and Performances

- IGBT Based Rectifier
- True Online Double Conversion with DSP Control Technology for High Performance and Reliability.
- New Graphical LCD Display Provides UPS Data, Alarms and Helps in faults diagnostics and trouble shooting.
- Double Conversion Efficiency upto 90%.
- Active Input Power Factor Correction 0.99.
- 0.8 Output Power Factor.
- Wide Input Voltage window (110 280 Vac) for Indian Environmental Condition and for Optimized Battery Performance.
- Configurable Output Voltage (200/208/220/230/240 Vac.)
- Generator Compatible with Wide Input Frequency Range (40 Hz-70 Hz).
- 4 Stage Extendable Charging Design for optimized Battery Performance.
- Adjustable Battery Charging Current 1/2/4/6 Amps according to Battery Capacity and Rating.
- 50/60 Hz Automatic Frequency Converter Mode.
- Intelligent Monitoring with Standard RS232/USB Port Plus Slot Available for RS485/Dry Contact/SNMP Card.
- Inbuilt OVCD.



Liebert GXT MT+ CX is a full feature Transformer free UPS designed to offer Compact, Efficient and Reliable solution to Modern Electronic Gadgets. It features True Double Conversion On Line Back UP Power Solution for Small Data Centre, Data Networks, Voice Networks and Process Automation Equipments.

Liebert GXT MT+ CX provides customers with a reliable source of uninterruptible power even in Harsh power environments, including very wide input voltage/Frequency window, Better output voltage regulation, frequency regulation, internal bypass, and input power factor correction and Low THDi.

Application

- Data Networks : Mid Range Servers (Windows and Linux), Wifi Applications and Data Networks.
- Small Data Centre Rooms: Small Data Centres Room to Manage Small Office Networks and Business Critical Continuity.
- Voice Networks: Cellular Sites, Voice Over IP (VOIP), Very Small Aperture Terminals (VSAT) PBX and IT Enabled PBX.
- Process Automation Equipments: Programmable Logic Controllers (PLC) and Cash Machines (ATM.)



Communication And Option

Advanced LCD Display.

 $New\,Graphical\,Display\,which\,Display\,UPS\,Parameters, Fault\,Codes, Alarms$

Fault Type is clearly mentioned on the display for fast diagnostic.

LCD display Provides Maximum operational Convenience while Managing the UPS.

Flexible Configuration

Extended Run Time ready facilitated through a simple process of building up additional battery resources.

 $\label{lem:multiple} \textbf{Multiple} \ \textbf{AC} \ \textbf{output} \ \textbf{interfaces} \ \textbf{via} \ \textbf{IEC} \ \textbf{standard} \ \textbf{sockets} \ \textbf{with} \ \textbf{programmable} \ \textbf{output}.$

SNMP Card

Network Monitoring SNMP Card, Used for Remote TCP/IP Web Monitoring, Supporting Remote Shutdown.

Dry Contact Card

Dry Contact for UPS, Providing Four Relay signal Output.

ModBus Card


Select it when UPS Needs to communicate with Building Management System.

Intelligent Management functions

- Remote Monitoring is available through USB/RS232 and optional via dry contacts and SNMP. The monitoring option software support TCP/IP with event log and analysis function.
- Self-diagnosis and protection enable the auto shutdown of the client terminal or server auto shutdown of the client terminal or server under abnormal mains supply or when battery is over discharged.
- SNMP Manager Card with advanced viewpower Softer (Optional): allows remote monitoring thro' Rj45 & manages mulitple UPS from anywhere thro' internet. Data logging Real time dynamic graphs of UPS data, warning notification via audible alarm, broadcast, mobile message, email & SNMP traps. Also supports optional environmental monitoring detector for temperature, humidity and smoke. Password security protection and remote access management.



LCD Display of Liebert GXT=MT+



Liebert GXT MT+ CX 1/2/3 kVA Technical Specifications

PHASE Single phase with ground CAPACITY* 1000 VA / 800 W 2000 VA / 1600 W 3000 VA / 240 INPUT Nominal Voltage 200/208/220/230/240VAC Input Voltage Range 40Hz ~ 70 Hz Power Factor ≥ 0.99 @ Nominal Voltage (100% load) OUTPUT Output Voltage 200/208/220/230/240VAC Voltage Regulation ± 1% Frequency Range (Synchronized Range) 47~ 53 Hz or 57~ 63 Hz Frequency Range (Batt. Mode) 50 Hz or 60Hz ± 0.1 Hz Current Crest Ratio 3:1 Harmonic Distortion ≤ 3 % THD (Linear Load) Transfer Imput Inverter to Bypass 4 ms (Typical) Waveform (Batt. Mode) Pure Sinewave	0 W
INPUTNominal Voltage200/208/220/230/240VACInput Voltage Range110-280 VAC (Based on load at 50%)Frequency Range40Hz ~ 70 HzPower Factor≥ 0.99 @ Nominal Voltage (100% load)OUTPUTOutput Voltage200/208/220/230/240VACVoltage Regulation± 1%Frequency Range (Synchronized Range)47~ 53 Hz or 57~ 63 HzFrequency Range (Batt. Mode)50 Hz or 60Hz ± 0.1 HzCurrent Crest Ratio3:1Harmonic Distortion≤ 3 % THD (Linear Load)Transfer Tansfer TimeAC to DCZeroInverter to Bypass4 ms (Typical)	0 W
INPUTNominal Voltage200/208/220/230/240VACInput Voltage Range110-280 VAC (Based on load at 50%)Frequency Range40Hz ~ 70 HzPower Factor≥ 0.99 @ Nominal Voltage (100% load)OUTPUTOutput Voltage200/208/220/230/240VACVoltage Regulation± 1%Frequency Range (Synchronized Range)47~ 53 Hz or 57~ 63 HzFrequency Range (Batt. Mode)50 Hz or 60Hz ± 0.1 HzCurrent Crest Ratio3:1Harmonic Distortion≤ 3 % THD (Linear Load)Transfer Tansfer TimeAC to DCZeroInverter to Bypass4 ms (Typical)	
Input Voltage Range110-280 VAC (Based on load at 50%)Frequency Range40Hz ~ 70 HzPower Factor≥ 0.99 @ Nominal Voltage (100% load)OUTPUTOutput Voltage200/208/220/230/240VACVoltage Regulation± 1%Frequency Range (Synchronized Range)47~53 Hz or 57~63 HzFrequency Range (Batt. Mode)50 Hz or 60Hz ± 0.1 HzCurrent Crest Ratio3:1Harmonic Distortion≤ 3 % THD (Linear Load)Transfer AC to DCZeroTimeInverter to Bypass4 ms (Typical)	
Input Voltage Range110-280 VAC (Based on load at 50%)Frequency Range40Hz ~ 70 HzPower Factor≥ 0.99 @ Nominal Voltage (100% load)OUTPUTOutput Voltage200/208/220/230/240VACVoltage Regulation± 1%Frequency Range (Synchronized Range)47~53 Hz or 57~63 HzFrequency Range (Batt. Mode)50 Hz or 60Hz ± 0.1 HzCurrent Crest Ratio3:1Harmonic Distortion≤ 3 % THD (Linear Load)Transfer AC to DCZeroTimeInverter to Bypass4 ms (Typical)	
Frequency Range 40Hz ~ 70 Hz Power Factor ≥ 0.99 @ Nominal Voltage (100% load) OUTPUT Output Voltage 200/208/220/230/240VAC Voltage Regulation ± 1% Frequency Range (Synchronized Range) 47~ 53 Hz or 57~ 63 Hz Frequency Range (Batt. Mode) 50 Hz or 60Hz ± 0.1 Hz Current Crest Ratio 3:1 Harmonic Distortion ≤ 3 % THD (Linear Load) Transfer AC to DC Zero Inverter to Bypass 4 ms (Typical)	
Power Factor ≥ 0.99 @ Nominal Voltage (100% load) OUTPUT 200/208/220/230/240VAC Voltage Regulation ± 1% Frequency Range (Synchronized Range) 47~53 Hz or 57~63 Hz Frequency Range (Batt. Mode) 50 Hz or 60Hz ± 0.1 Hz Current Crest Ratio 3:1 Harmonic Distortion ≤ 3 % THD (Linear Load) Transfer Tansfer Time AC to DC Time Inverter to Bypass	
OUTPUT Output Voltage 200/208/220/230/240VAC Voltage Regulation ± 1% Frequency Range (Synchronized Range) 47~53 Hz or 57~63 Hz Frequency Range (Batt. Mode) 50 Hz or 60Hz ± 0.1 Hz Current Crest Ratio 3:1 Harmonic Distortion ≦ 3 % THD (Linear Load) Transfer AC to DC Zero Time Inverter to Bypass 4 ms (Typical)	
Voltage Regulation ± 1% Frequency Range (Synchronized Range) 47~ 53 Hz or 57~ 63 Hz Frequency Range (Batt. Mode) 50 Hz or 60Hz ± 0.1 Hz Current Crest Ratio 3:1 Harmonic Distortion ≦ 3 % THD (Linear Load) Transfer AC to DC Zero Time Inverter to Bypass 4 ms (Typical)	
Voltage Regulation ± 1% Frequency Range (Synchronized Range) 47~ 53 Hz or 57~ 63 Hz Frequency Range (Batt. Mode) 50 Hz or 60Hz ± 0.1 Hz Current Crest Ratio 3:1 Harmonic Distortion ≦ 3 % THD (Linear Load) Transfer AC to DC Zero Time Inverter to Bypass 4 ms (Typical)	
Frequency Range (Synchronized Range) 47~ 53 Hz or 57~ 63 Hz Frequency Range (Batt. Mode) 50 Hz or 60Hz ± 0.1 Hz Current Crest Ratio 3:1 Harmonic Distortion ≦ 3 % THD (Linear Load) Transfer Time AC to DC Inverter to Bypass 4 ms (Typical)	
Frequency Range (Batt. Mode) 50 Hz or 60Hz ± 0.1 Hz Current Crest Ratio 3:1 Harmonic Distortion ≦ 3 % THD (Linear Load) Transfer AC to DC Zero Time Inverter to Bypass 4 ms (Typical)	
Current Crest Ratio 3:1 Harmonic Distortion ≦ 3 % THD (Linear Load) Transfer AC to DC Zero Time Inverter to Bypass 4 ms (Typical)	
Harmonic Distortion ≦ 3 % THD (Linear Load) Transfer Time AC to DC Zero Inverter to Bypass 4 ms (Typical)	
Transfer AC to DC Zero Time Inverter to Bypass 4 ms (Typical)	
Time Inverter to Bypass 4 ms (Typical)	
EFFICIENCY	
To AC Mode 88% 90%	
To Battery Mode 83% 85% 88%	
BATTERY	
Battery Type 12 V / 9 AH 12 V / 9 AH 12 V / 9 AH	-
Numbers 2 4 6	
Standard Typical Pacharga Time 4 hours recover to 90% capacity	
Model Charging Current (max.) 1.0 A	
Charging Voltage 27.4VDC ± 1% 54.7 VDC ±1% 82.1 VDC ±	%
Battery Type Depending on the capacity of external batteries	
Long-run Numbers 3 6 6	
Model* Charging Current (max.) 1.0A/2.0A/4.0A/6.0 A, 6.0A default	
Charging Voltage 41.0VDC ± 1% 82.1 VDC ±1% 82.1 VDC ±	%
INDICATORS	
LCD Load level, Battery level, AC mode, Battery mode, Bypass mode, and Fault ind	cators
ALARM	
Battery Mode Sounding every 4 seconds	
Low Battery Sounding every second	
Overload Sounding twice every second	
Fault Continously sounding	
PHYSICAL	
Standard Dimension, D x W x H (mm) 282 x 145 x 220 397 x 145 x 220 421 x 190 x 3	18
Model Net Weight (kgs) 9.8 17 27.6	
Long-run Dimension, D x W x H (mm) 282 x 145 x 220 397 x 145 x 220	
Model** Net Weight (kgs) 4.1 6.8 7.4	
ENVIRONMENT	
Humidity 20-90 % RH @ 0-40°C (non-condensing)	
Noise Level Less than 50dBA @ 1 Meter	
MANAGEMENT	
Smart RS-232/USB Supports Windows 2000/2003/XP/Vista/2008/7/8, Linux, Unix, and MA	
Optional SNMP Power management from SNMP manager and web browser	

 $^{^*}$ Derate to 80% of capacity in Frequency converter mode, the output voltage is adjusted to 100/200/208VAC and the ambient temperature during 35°C to 50°C.

^{**} Product specifications are subject to change without further notice

Country Office

Emerson Network Power (India) Private Ltd. Plot No. C-20, Road No. 19, Wagle Estate, Thane (W), Maharashtra - 400 604. India.

Tel.: 91-22-33154400 Fax: 91-22-25828358

Toll Free No 18002096070

Email: marketing.india@emerson.com



CIO CHOICE 2014 Awards (Centre Of Recognition & Excellence) Most Preferred Brand

- · Integrated Data Center Solution
- ICT Infrastructure Cooling
 Data Center Infrastructure Management



Frost & Sullivan 'Voice Of Customer' 2013

- · Most Preferred UPS Brand IT/ITES
- Most Preferred UPS Brand Manufacturing & Process Industries
 Most Preferred UPS Brand Power, Oil and Gas
- Overall Customer Service Leadership (Above 20kVA) Award



CIO CHOICE 2013 Awards (Centre Of Recognition & Excellence) - Most Preferred Brand

- Data Center (UPS) · Data Center (Cooling)
- Power Distribution
 Infrastructure Appliance

2013 (Global recognition) EMA Radar Report™

for Data Center Infrastructure Managemer 'Most Comprehensive DCIM Solution' - Trellis

2012 (Global recognition)

Forrester's March 2012: "Market Overview: Data Center Infrastructure Management Solutions" report 'Dominant supplier in data center infrastructure management (DCIM)



Frost & Sullivan 'Asia Pacific Market Share Leadership 2012' data centre cooling solutions market 2010 Frost & Sullivan

'India UPS Market Leadership Award'







While every precaution has been taken to ensure accuracy and completeness in this brochure, Emerson Network Power assumes no responsibility, and disclaims all liability for damages resulting from use of this information or for any errors or omissions.

For disposal of Batteries Please visit the below link: http://www.cpcb.nic.in/divisionsofheadoffice/hwmd/lead.pdf

Note: Specifications & Features may vary based on the condition.

Emerson Network Power.

The global leader in enabling Business-Critical Continuity[™].

AC Power Embedded Computing Outside Plant

Racks & Integrated Cabinets

www.emersonnetworkpower.com

Connectivity DC Power

Embedded Power Monitoring

Power Switching & Controls **Precision Cooling**

Services Surge Protection

Emerson, Business - Critical Continuity and Emerson Network Power are trademarks of Emerson Electric Co. or its affiliated companies. © 2012 Emerson Electric Co.